brother
at your side

Your efficient 3-in-1 mono laser multifunction printer

Easy to set up and connect with fast flawless printing

DCP-L2660DW

PRINT SCAN COPY 5GHz WIRELESS

www.brother.co.uk

Midland Business Equipment Ltd
4-8 Station Road, Knowle, Solihull,
West Midlands B93 0HT

Tel : 01564 776198
Email : info@midlandbusinessequipment.co.uk
Website: www.midlandbusinessequipment.co.uk

Your efficient 3-in-1 mono laser printer

Work smarter from anywhere at home or in the office with the easily connected DCP-L2660DW. Hosting a range of efficiency-boosting features, this 3-in-1 mono laser printer saves you time with fast flawless printing and quick scan speeds, automatic 2-sided print, a generous paper tray capacity and large automatic document feeder (ADF).

Get set up with ease and download the Brother Mobile Connect app, enabling you to print and scan from virtually anywhere.

DCP-L2660DW

Key features:

- Print up to 34 pages per minute (ppm)
- 2-sided print, up to 16 sides per minute (spm)
- Scan up to 22.5 images per minute[3]
- 6.8cm colour touchscreen
- Fast ethernet, 5GHz Wi-Fi and USB
- 256MB internal memory
- 50 sheet ADF[11]
- 250 sheet paper input tray[11]
- Comes with 1,200 page yield toner. 3,000 maximum yield available[7]

Work smarter

The DCP-L2660DW is designed to increase efficiency, with fast print speeds helping you to work smarter. The ADF and 2-sided print feature save you time, allowing you to get on with other tasks. Scan your documents in colour or mono and send directly to your desktop or mobile device.

Effortless

Make your day easier and your printing effortless, with simple set up and fast ethernet, 5GHz Wi-Fi or USB connection. This efficient DCP-L2660DW is a breeze to operate using the easy to navigate menu on the 6.8cm colour touchscreen. Benefit from the ability to create custom shortcuts on the touchscreen for your most used functions.

The perfect partner

High quality print technology ensures that your output is flawless and professional every time. The expertly designed DCP-L2660DW has high capacity paper input and output trays allowing you to print for longer, while the compact and quiet form enables you to work without interruption in smaller workspaces.

Print longer

The DCP-L2660DW keeps your printing costs down using a separate drum and 1,200 page toner, supporting your higher print volume needs. Toner is easy to change and high yield toner is available, printing up to 3,000 pages[7], reducing your cost per page and frequency to replace.

Secure by design

To keep pace with the ever-evolving legislation on privacy and data security, our devices offer the latest industry-standard security features to securely protect your data. Our security experts continuously research new enhancements to products, solutions and services to proactively ensure all our products are 'secure by design'.

The DCP-L2660DW provides a range of robust features. It uses triple-layer security at a device, network and document level. This offers added peace of mind and guarantees that the integrity of your data is maintained at every step.

Print from anywhere

With Brother Mobile Connect, you can fully operate your Brother printer from your fingertips. Print and scan documents on the move and order genuine Brother supplies straight to your door. You can also personalise your frequently used features and unlock a revolutionary way of printing from your mobile device.

Download the app on your mobile device to get started.

ecopro

The automated toner subscription for your printer

Whether you print a little or a lot, we have a flexible printing subscription plan to suit everyone. You can sign up and enjoy toner supplies delivered automatically with free postage direct to your doorstep.

Benefit from ongoing printer warranty cover, free toner recycling and first-class customer support. Subscribe to a better way to print.



TO FIND OUT MORE

Download the Brother Mobile Connect app or visit the website: brother.co.uk/ecopro

General

Technology
Electrophotographic laser

Memory
256MB

Control panel
6.8cm colour
touchscreen LCD

Local interface
Hi-Speed USB 2.0

Wired network
Fast ethernet

Wireless network
2.4GHz and 5GHz support

Carton contents
Device, in-box toner, drum, power supply cord, quick set-up guide, warranty card

Print

Print speed (A4)
1-sided: 34ppm mono
2-sided: 16spm mono

First print out time (FPOT)
Up to 8.5 seconds mono

Quiet mode
A mode to reduce the printing noise

Resolution
Up to 1200 x 1200dpi

Print languages
PCL6, BR-Script3,
PDF Version 1.7

Embedded fonts (PCL)
73 scalable fonts,
12 bitmap fonts

Embedded barcodes (PCL)
16 bar codes*
*Code39, Interleaved 2 of 5, FIM (US-PostNet), Post Net (US-PostNet), EAN-8, EAN-13, UPC-A, UPC-E, Codabar, ISBN EAN), ISBN UPC-E), Code128 (set A, set B, set C), EAN128 (set A, set B, set C), Code93, GS1Databar, MSI

Embedded fonts (Postscript)
66 scalable fonts

Printer functions

N-up printing
Reduce up to 25 pages into a single page

Poster printing
Enlarge a single page into a poster using 2x2, 3x3, 4x4 or 5x5 pages

Toner save mode
Use the toner save mode to reduce toner consumption without affecting print speed

Watermark printing
Watermark your documents with predefined text, custom logo or custom messages

ID printing
Add identification to your printed documents (date and time, short custom message or PC username)

Booklet printing
Print documents in A5 booklet format using automatic or manual 2-sided print

Print profiles
Store your favourite driver settings as profiles to easily recall them

Manual 2-sided print
Manual 2-sided printing (recommended for media not supported by automatic 2-sided print)

Reverse print
Rotate the content of a printed document by 180°

Print complete notice
A printing notification can be set to go to your computer (network only)

Printer driver

Windows
Windows 10 (32 and 64 bit)
Windows 11(64 bit)
and more

macOS
Printing via macOS requires the use of AirPrint. Mac drivers are not provided.

Linux
CUPS, LPD/LPRng
(x86/x64 environment)

ChromeOS
Supports native ChromeOS printing

PCL driver
Universal printer driver (Windows)
(PCL5e/BRScript)

PostScript Universal printer driver
Driver for Windows that enables you to print to any network or locally connected Brother printer

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Paper handling[11]

Paper input:
Standard tray
250 sheets

Manual feed slot
1 sheet

ADF
50 sheets

Paper output
120 sheets A4

Envelope printing
Yes, from manual feed slot

Media sizes:
Standard tray
A4, Letter, B5(JIS), B5(ISO), A5, A5(Long Edge), B6(JIS), A6, Executive, A4 Short, 16K(195x270mm)

Manual feed slot
Width: 76.2 to 215.9 mm,
Length: 127 to 355.6 mm
Envelope: COM-10, DL, C5, Monarch

ADF
Width: 105 to 216 mm
Length: 147 to 356 mm

Scanner glass
Up to A4/LTR

Auto 2-sided
A4

Media type and weights:
Standard tray
Plain paper, thin paper, recycled paper, thick paper
60-163gsm

Manual feed slot
Plain paper, thin paper, thick paper, thicker paper, recycled paper, bond, label, envelope, env. thin, env. thick
60-230gsm

ADF
Plain paper, recycled paper
60 to 105gsm

Auto 2-sided
Plain paper, thin paper, recycled paper
60-105gsm

Mobile and Web connectivity

Brother Mobile Connect[17] (Android)
Print from, scan to, preview copies and check the machine status from an Android device

Brother Mobile Connect[17] (iPad / iPhone)
Print from, scan to, preview copies and check the machine status from an iPad / iPhone

Apple AirPrint[17]
Print from and scan to most common file types from any AirPrint enabled application

Brother Print Service Plugin[17]
Print from an Android device without a dedicated App.

Mopria™ [17]
Print most common file types from Mopria™ supported Android devices

Brother Apps[18]
Scan to Mobile, Scan to Searchable PDF, Scan to PowerPoint, Scan to Excel, Scan to Word, Easy scan to E-mail, Cloud Secure Print, Email Print

Web Connect[18]
Print from and scan to without using a PC on Box, Dropbox, Evernote, OneDrive, Google Drive™ OneNote, SharePoint online

Copy

Copy speed (A4)
1-sided: 34 copies per minute mono

Resolution
Up to 600 x 600dpi

First copy out time (FCOT)
Up to 10 seconds mono

Greyscale
256 shades of grey
(8 bit for each colour)

Copy functions

Multi-copying/stack/sort
Makes up to 99 copies of each page/stacks or sorts

Enlargement/reduction ratio
Reduce or increase document sizes from 25% to 400% in 1% increments

2 in 1 ID copying
Allows the user to copy both sides of an ID card to a single A4 sheet

N in 1 copying
Allows the user to compress 2 or 4 pages on to a single A4 sheet

Scan

Scanner type
Contact image sensor (CIS)

Colour and mono scanning
Yes

Scan speed (A4)[3]
1-sided: 22.5ipm mono and 7.5ipm colour

Scan resolution from ADF
600 x 600dpi

Scan resolution from scanner glass
1200 x 1200dpi

Interpolated scan resolution
Brother Scanner Utility enhances up to 19,200 x 19,200dpi

Colour depth
30 bit colour processing (input)
24 bit colour processing (output)

Greyscale
10 bit colour processing (input)
8 bit colour processing (output)

Scanner functions

Supported file formats
Including PDF (PDF/A, Secure PDF, Signed PDF, Searchable[17]) JPEG,TIFF

Standard functions[17]
Scan to e-mail, OCR , image, file

Network scanning[16]
Scan to FTP, FTPS, HTTPS, Sharepoint server (iPrint&Scan for Windows only)

Scan features
Auto deskew from ADF only (iPrint&Scan for desktop)

Scan to Microsoft Office
Scan to Word (.docx), PowerPoint (.pptx), Excel (.xlsx) for Microsoft Office

Scan profile[15]
Create up to 25 profiles for an easy way to store multiple scan settings (scan to FTP/ Sharepoint)

Document separation
Create scanned files based on blank sheet separation or a specific number of single sided images or sheets of paper, even if more documents are set on the ADF

Scanner drivers

Windows
TWAIN and WIA
Windows 10 (32 bit)
Windows 11 (32 and 64 bit)

macOS
Scanning via macOS requires the use of AirPrint. Mac drivers are not provided.

Linux
SANE (32 and 64 bit editions)

ChromeOS
Supports native ChromeOS scanning

Visit support.brother.com for the full list of supported OS and to download the latest drivers and software.

Fleet management tools

BRAdmin[16,17]
LAN/WAN management software

Embedded web server
Web based print management software embedded onto the device

Driver Deployment Wizard[16,17]
Easily create print drivers for hassle free deployment over your network

Status monitor[16]
Monitor the status of your machine from your computer

Software

Brother iPrint&Scan Desktop[15,17]
Print from, scan to, preview copies and check the machine status from Windows or macOS PC

PaperPort SE 14[16,17]
Document management and sharing program from KOFAX

Utilities
Provides setup guides, manual, FAQ, troubleshooting and contact to Brother customer service

Easy setup
Simple access to drivers and software for the installation of your Brother machine from support.brother.com

Connectivity

Wired network
Fast ethernet (10Base-T/100Base-TX)

Wireless network
2.4GHz: IEEE 802.11 b/g/n (Infrastructure Mode)
IEEE 802.11 g/n (Wi-Fi Direct)

5GHz: IEEE 802.11 a/n (Infrastructure Mode)
IEEE 802.11 a/n (Wi-Fi Direct)

Wi-Fi Direct®
Print wirelessly without having to go through a wireless access point (both automatic and manual methods supported)

Wireless setup support
Wi-Fi Protected Setup (WPS)

Wireless applications
Vertical pairing

Mobile
Print or scan from your mobile device with Brother Mobile Connect, Airprint, Mopria

Local interface
Hi-Speed USB 2.0

Security features

Wired network security
SMTP-AUTH, SSL/TLS(SMTP, HTTP, IPP, FTP), SNMP v3, 802.1x (EAP-MD5, EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), OAuth(SMTP, POP3, IMAP4)

Wireless network security
WEP 64/128 bit, WPA-PSK(TKIP/AES), WPA2-PSK (TKIP/AES), WPA3-SAE (AES), WiFi Direct supports WPA2-PSK(AES) only.

SMTP-AUTH, SSL/TLS (SMTP,HTTP,IPP,FTP), SNMP v3, 802.1x (EAP-FAST, PEAP, EAP-TLS, EAP-TTLS), OAuth(SMTP, POP3, IMAP4)

IPv4
ARP, RARP, BOOTP, DHCP, APIPA(Auto IP), WINS/NetBIOS name resolution, DNS Resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/ Port9100, SMTP Client, IPP/ IPPS, FTP Client and Server, SNMPv1/v2c/v3, HTTP/HTTPS server, TFTP client and server, ICMP, Web Services (Print/ Scan), SNTP Client

IPv6
NDP, RA, DNS resolver, mDNS, LLMNR responder, LPR/LPD, Custom Raw Port/Port9100, IPP/IPPS, SMTP Client, FTP Client and Server, SNMPv1/v2c/ v3, HTTP/HTTPS server, TFTP client and server, ICMPv6, Web Services (Print/Scan), SNTP Client

IP filter
Restrict which network users can or cannot access the device over the network (IPv4 only)

E-mail notifications
Automatically have the device send e-mail alerts when it requires attention, such as when the toner is low or needs replacing

E-mail reports
Receive usage reports on a regular basis via e-mail

Automatic intrusion detection
All Brother Print devices are secure by design. Devices automatically recognise security attacks and take preventative measures, including rebooting where necessary, to ensure the device remains secure

Firmware updates
In addition to allowing automatic update alerts to install the latest version the printer can be set to not receive older firmware versions to avoid downgrade by an unauthorised user

Cloud secure print
Enables password protected driverless print job release

Certificate management
Use the default standard self-signed, create a custom self-signed certificate, certificate signing request (CSR), or external public cerificate and private key for protected network

Digitally-signed firmware
The firmware for Brother print and scan devices is digitally signed and secure

Port-based network access control
(IEEE 802.1x)
Brother devices are in full compliance with this standard, to allow connection to an 802.1x EAP (Extensible Authentication Protocol) protected network

Restrict network protocols
The Protocol Control feature allows an administrator to restrict communication protocols (e.g. FTP, Telnet) as required

Supplies and consumables

In-box toner[7]
1 x 1,200 pages (BK)

Standard yield toner[7]
TN2510 - 1,200 pages

High yield toner[7]
TN2510XL - 3,000 pages

Drum unit
DR2510 - approx 15,000 pages at 1 pages per job

Dimensions and weights

With carton (WxDxH)
515 x 578 x 428 -14.4kg

Without carton (WxDxH)
410 x 399 x 319mm - 11.4kg

Duty cycle

Recommended monthly
Up to 2,500 pages

Operating environment

Power requirement
220-240V
AC 50/60Hz

Operating environment
Humidity 20 - 80 %
10°C - 32.5°C
50°F - 90.5°F

Storage environment
Humidity 35 - 85 %
0°C - 40°C
32°F - 104°F

Environment

Approx power consumption[13,23]
Copying: 490W
Copying in quiet mode: 280W
Printing: 470W
Printing in quiet mode: 270W
Ready: 43W
Sleep: 4.1W
Deep sleep: 0.7W
Power Off: 0.10W

TEC value
0.39 kWh/week

Sound power[12]
Printing: 6.63B(A)
Ready: Inaudible
Quiet mode: 6.12B(A)
Deep sleep: Inaudible

Sound pressure[12]
PC printing (mono):
Approx. 49.0dB(A)
Ready: 30.0dB(A)
Quiet mode: 44.0dBA)

Toner save
This reduces the toner consumption to get more pages from your consumables

Blue Angel
Yes

GS Mark
Yes

Nordic Swan
Yes

3 Scan Speeds based on ISO/IEC 17991
7 Approx. declared yield value in accordance with ISO/IEC 19752
11 Capacity calculated with 80gsm paper
12 Sound pressure and sound power level in accordance with ISO 7779
13 Power consumption power off is measured according to IEC 62301 Edition 2.0
15 Windows and macOS only
16 Windows only
17 Optional download
18 Requires an Internet connection
23 Power consumption is measured using ENERGY STAR Ver 3.1 test method network configuration

Compatible with Brother's EcoPro toner subscription

Brother Earth

Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth.
www.brotherearth.com

All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

CD4208

brother at your side